




























# Antenna Adapter Selection Matrix











For City Theatrical Wireless DMX Products

	Standard Antennas:				Long Range Antennas:		Accessories:	Legacy Antennas:	
<b>P/N:</b>	5729	5980	5983	5984	5981	5982	5637	5731	5732
<b>Gain (dBi):</b>	2dBi	2dBi/4dBi	2.5dBi/2.5dBi	1.8dBi/3.8dBi	6.8dBi/8.5dBi	11dBi	Antenna Splitter, 3 N-Connectors (Female)	4dBi	4.5dBi
<b>Frequency:</b>	2.4GHz	900MHz/2.4GHz	900MHz/2.4GHz	900MHz/2.4GHz	900MHz/2.4GHz	900MHz/2.4GHz		2.4GHz	2.4GHz
<b>Product Name:</b>	Antenna, Indoor Omni, 2.3"	Antenna, Omni Broadband	Antenna, Omni Broadband	Antenna, Omni Broadband "Stubby"	Antenna, Panel	Antenna, Yagi		Antenna, Indoor Omni (Legacy)	Antenna, Outdoor Omni (Legacy)
									

## Multiverse Wireless DMX Products:

 5900 Multiverse® SHoW Baby	Standard; no adapter needed.							
 5902 Multiverse Node 900MHz/2.4GHz								
5903 Multiverse Node 2.4GHz								
 5910 Multiverse Transmitter 900MHz/2.4GHz		Standard; no adapter needed.			Requires 5638 Adapter Cable RSMA-Male to N-Male 	Requires two 5641 Adaptor Cables, N-Male to N-Male, and one 5638 Adapter Cable RSMA-Male to N-Male  		
5911 Multiverse Transmitter 2.4GHz								
5912 Multiverse Transmitter 900MHz								
 5904 Multiverse Studio Receiver 900MHz/2.4GHz								
5905 Multiverse Studio Receiver 2.4GHz								
 5906 Multiverse Receiver Card 2.4GHz w/ Internal Antenna	Requires the 103-00730 Cable	Requires the 103-00730 Cable	Requires the 103-00730 Cable and 5638 Adapter Cable	Requires the 103-00730 Cable	Requires the 103-00730 Cable and 5638 Adapter Cable  	Requires the 103-00730 Cable, 5938 Adapter Cable, and 5641 Antenna Adapter Cable   		
5907 Multiverse Receiver Card 900MHz w/ Internal Antenna								
 7400-5902 Multiverse Vero Transceiver 900MHz/2.4GHz			Standard; no adapter needed.		Requires 5641 Adaptor Cable N-Male to N-Male 	Requires three 5641 Adaptor Cables, N-Male to N-Male   		
7400-5903 Multiverse Vero Transceiver 2.4GHz								

## Legacy Wireless DMX Products:

 5702M SHoW DMX SHoW Baby® 6 (Legacy)	Standard; no adapter needed.							
 5701 SHoW DMX Neo® Transmitter (Legacy)					Requires 5638 Adapter Cable RSMA-Male to N-Male 	Requires two 5641 Adaptor Cables, N-Male to N-Male, and one 5638 Adapter Cable RSMA-Male to N-Male  	Standard; no adapter needed.	
5711 SHoW DMX Neo Receiver (Legacy)								
 7400-5707 SHoW DMX Vero® (Legacy)					Requires 5641 Adaptor Cable N-Male to N-Male 	Requires three 5641 Adaptor Cables N-Male to N-Male   	Standard; no adapter needed.	
7400-5708 SHoW DMX Vero Net (Legacy)								

### Instructions:

1. Select a device from the left column.
2. The row for that device will indicate which adapters are necessary to use each antenna/adaptor listed in the top row.
3. If the cell is gray, that antenna will not work with your selected device.

Reference:

