

CITY

THEATRICAL

NEW YORK • LONDON

Installing a firmware update in the CTI 5904 or 5905 Multiverse® Studio Receiver

To install a firmware update:

Download the new firmware .zip file from the CTI Website. It can be found in the download section of the product page.

You will need a PC or Mac to plug into the Studio's USB-C connector. When in boot load mode, the Studio's USB port will act as a flash drive for you to copy the files to.

1. Enter boot load mode on the Studio by:
 - a. Selecting "Update Firmware" from menu screen
 - OR**
 - b. Turn the unit power on while holding down the "Up" button. Keep it pressed until the screen displays the update instructions.
2. Delete any files that already exist on the Studio's flash drive when it shows up on your computer
3. Un-zip the downloaded file and transfer all firmware files to the root directory of the Studio's drive.
4. Press the "Up" button after all files have been copied to begin the update process
5. Wait for all firmware files to be programmed as indicated on the screen.
6. Once complete, if successful, the Studio will re-boot into normal mode, otherwise the errors will be indicated on the screen.

US HEADQUARTERS
475 BARELL AVENUE
CARLSTADT, NEW JERSEY 07072
TEL 800 230 9497 / 201 549 1160
FAX 201 549 1161

www.citytheatrical.com

LONDON OFFICE
UNIT 1-3 WYVERN ESTATE, BEVERLEY WAY
NEW MALDEN, SURREY KT3 4PH
TEL +44 (0) 20 8949 5051
FAX +44 (0) 20 7183 6061